



# DMX Control Modes

## Standard Mode

Standard Mode		
CH	Value	Function
1	0 – 255	<b>Pan</b>
2	0 – 255	<b>Pan fine</b>
3	0 – 255	<b>Tilt</b>
4	0 – 255	<b>Tilt fine</b>
5	0 – 255	<b>Color wheel</b> (See color wheel table)
6	0 – 255	<b>Red</b>
7	0 – 255	<b>Green</b>
8	0 – 255	<b>Blue</b>
9	0 – 255	<b>White</b>
10	0 – 255	<b>Shutter effects</b> (See shutter effects table)
11	0 – 255	<b>Dimmer</b>
12	0 – 255	<b>CTO</b>
13	0 – 255	<b>Zoom</b>
14	0 – 255	<b>LED ring color wheel</b> (See color wheel table)
15	0 – 255	<b>LED ring shutter</b> (Shutter effects same as LED pixels)
16	0 – 255	<b>LED ring dimmer</b>
17	0 – 255	<b>Pattern</b>
18	0 – 255	<b>Pattern speed</b>
19	0 – 255	<b>LED ring pattern</b>
20	0 – 255	<b>LED ring pattern speed</b>
21	0 – 255	<b>Control</b>
22	0 – 255	<b>Remote DMX address</b>

# DMX Control Modes

## Advanced Mode

Advanced Mode		
CH	Value	Function
1	0 – 255	<b>Pan</b>
2	0 – 255	<b>Pan fine</b>
3	0 – 255	<b>Tilt</b>
4	0 – 255	<b>Tilt fine</b>
5	0 – 255	<b>Color wheel</b> (See color wheel table)
6	0 – 255	<b>Red</b>
7	0 – 255	<b>Red fine</b>
8	0 – 255	<b>Green</b>
9	0 – 255	<b>Green fine</b>
10	0 – 255	<b>Blue</b>
11	0 – 255	<b>Blue fine</b>
12	0 – 255	<b>White</b>
13	0 – 255	<b>White fine</b>
14	0 – 255	<b>Shutter effects</b> (See shutter effects table)
15	0 – 255	<b>Dimmer</b>
16	0 – 255	<b>Dimmer fine</b>
17	0 – 255	<b>CTO</b>
18	0 – 255	<b>Zoom</b>
19	0 – 255	<b>Zoom fine</b>
20	0 – 255	<b>LED ring color wheel</b> (See color wheel table)
21	0 – 255	<b>LED ring red</b>
22	0 – 255	<b>LED ring green</b>
23	0 – 255	<b>LED ring blue</b>
24	0 – 255	<b>LED ring shutter</b> (Shutter effects same as LED pixels)
25	0 – 255	<b>LED ring dimmer</b>
26	0 – 255	<b>Pattern</b>
27	0 – 255	<b>Pattern speed</b>
28	0 – 255	<b>LED ring pattern</b>
29	0 – 255	<b>LED ring pattern speed</b>
30	0 – 255	<b>Control</b>
31	0 – 255	<b>Remote DMX address</b>



# DMX Control Modes

## Full Control Mode

Full Control Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Red fine
8	0 – 255	Green
9	0 – 255	Green fine
10	0 – 255	Blue
11	0 – 255	Blue fine
12	0 – 255	White
13	0 – 255	White fine
14	0 – 255	Shutter effects (See shutter effects table)
15	0 – 255	Dimmer
16	0 – 255	Dimmer fine
17	0 – 255	CTO
18	0 – 255	Zoom
19	0 – 255	Zoom fine
20	0 – 255	LED ring color wheel all (See color wheel table)
21	0 – 255	LED ring red all
22	0 – 255	LED ring green all
23	0 – 255	LED ring blue all
24	0 – 255	LED ring shutter (Shutter effects same as LED pixels)
25	0 – 255	LED ring dimmer
26	0 – 255	Red 1
27	0 – 255	Green 1
28	0 – 255	Blue 1
29	0 – 255	White 1
30	0 – 255	Shutter 1
31	0 – 255	Dimmer 1
...	...	Red ...
...	...	Green ...
...	...	Blue...
...	...	White...
...	...	Shutter...
...	...	Dimmer...

Continued in next page

# DMX Control Modes

## Full Control Mode (Continued)

CH	Value	Function
134	0 – 255	Red 19
135	0 – 255	Green 19
136	0 – 255	Blue 19
137	0 – 255	White 19
138	0 – 255	Shutter 19
139	0 – 255	Dimmer 19
140	0 – 255	LED ring 1, LED 1 red
141	0 – 255	LED ring 1, LED 1 green
142	0 – 255	LED ring 1, LED 1 blue
143	0 – 255	LED ring 1, LED 2 red
144	0 – 255	LED ring 1, LED 2 green
145	0 – 255	LED ring 1, LED 2 blue
...	...	LED ring ..., LED 1 red
...	...	LED ring ..., LED 1 green
...	...	LED ring ..., LED 1 blue
...	...	LED ring ..., LED 2 red
...	...	LED ring ..., LED 2 green
...	...	LED ring ..., LED 2 blue
158	0 – 255	LED ring 4, LED 1 red
159	0 – 255	LED ring 4, LED 1 green
160	0 – 255	LED ring 4, LED 1 blue
161	0 – 255	LED ring 4, LED 2 red
162	0 – 255	LED ring 4, LED 2 green
163	0 – 255	LED ring 4, LED 2 blue
164	0 – 255	Control
165	0 – 255	Remote DMX address



# DMX Control Modes

## Pixel Mapping Mode

Pixel Mapping Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	White
10	0 – 255	Shutter effects (See shutter effects table)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Zoom
14	0 – 255	LED ring color wheel all(See color wheel table)
15	0 – 255	LED ring red all
16	0 – 255	LED ring green all
17	0 – 255	LED ring blue all
18	0 – 255	LED ring shutter (Shutter effects same as LED pixels)
19	0 – 255	LED Ring dimmer
20	0 – 255	Red 1
21	0 – 255	Green 1
22	0 – 255	Blue 1
23	0 – 255	White 1
24	0 – 255	Shutter 1
25	0 – 255	Dimmer 1
...	...	Red ...
...	...	Green ...
...	...	Blue...
...	...	White...
...	...	Shutter...
...	...	Dimmer...
128	0 – 255	Red 19
129	0 – 255	Green 19
130	0 – 255	Blue 19
131	0 – 255	White 19
132	0 – 255	Shutter 19
133	0 – 255	Dimmer 19

Continued in next page

# DMX Control Modes

## Pixel Mapping Mode (Continued)

CH	Value	Function
134	0 – 255	<b>LED ring pattern</b>
135	0 – 255	<b>LED ring pattern speed</b>
136	0 – 255	<b>Control</b>
137	0 – 255	<b>Remote DMX address</b>



# DMX Control Modes

## Pattern Control Mode

Pattern Control Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	White
10	0 – 255	Shutter effects (See shutter effects table)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Zoom
14	0 – 255	LED ring color wheel (See color wheel table)
15	0 – 255	LED ring red all
16	0 – 255	LED ring green all
17	0 – 255	LED ring blue all
18	0 – 255	LED ring shutter (Shutter effects same as LED pixels)
19	0 – 255	LED ring dimmer
20	0 – 255	Red 1
21	0 – 255	Green 1
22	0 – 255	Blue 1
23	0 – 255	White 1
24	0 – 255	Shutter 1
25	0 – 255	Dimmer 1
26	0 – 255	Pattern 1
27	0 – 255	Pattern 1 speed
28	0 – 255	Red 2
29	0 – 255	Green 2
30	0 – 255	Blue 2
31	0 – 255	White 2
32	0 – 255	Shutter 2
33	0 – 255	Dimmer 2
34	0 – 255	Pattern 2
35	0 – 255	Pattern 2 speed
36	0 – 255	Red 3
37	0 – 255	Green 3

Continued in next page

# DMX Control Modes

## Pattern Control Mode (Continued)

CH	Value	Function
38	0 – 255	<b>Blue 3</b>
39	0 – 255	<b>White 3</b>
40	0 – 255	<b>Shutter 3</b>
41	0 – 255	<b>Dimmer 3</b>
42	0 – 255	<b>Pattern 3</b>
43	0 – 255	<b>Pattern 3 speed</b>
44	0 – 255	<b>LED ring P1-red</b>
45	0 – 255	<b>LED ring P1-green</b>
46	0 – 255	<b>LED ring P1-blue</b>
47	0 – 255	<b>LED ring P1-shutter</b> (Shutter effects same as LED pixels)
48	0 – 255	<b>LED ring P1-dimmer</b>
49	0 – 255	<b>LED ring P1-pattern</b>
50	0 – 255	<b>LED ring P1-pattern speed</b>
51	0 – 255	<b>LED ring P2-red</b>
52	0 – 255	<b>LED ring P2-green</b>
53	0 – 255	<b>LED ring P2-blue</b>
54	0 – 255	<b>LED ring P2-shutter</b> (Shutter effects same as LED pixels)
55	0 – 255	<b>LED ring P2-dimmer</b>
56	0 – 255	<b>LED ring P2-pattern</b>
57	0 – 255	<b>LED ring P2-pattern speed</b>
58	0 – 255	<b>Control</b>
59	0 – 255	<b>Remote DMX address</b>





# DMX Control Modes

## Compressed RGBW Mode

Compressed RGBW Mode		
CH	Value	Function
1	0 – 255	<b>Pan</b>
2	0 – 255	<b>Pan fine</b>
3	0 – 255	<b>Tilt</b>
4	0 – 255	<b>Tilt fine</b>
5	0 – 255	<b>Color wheel</b> (See color wheel table)
6	0 – 255	<b>Red</b>
7	0 – 255	<b>Green</b>
8	0 – 255	<b>Blue</b>
9	0 – 255	<b>White</b>
10	0 – 255	<b>Shutter effects</b> (See shutter effects table)
11	0 – 255	<b>Dimmer</b>
12	0 – 255	<b>Zoom</b>
13	0 – 255	<b>LED ring color wheel</b> (See color wheel table)
14	0 – 255	<b>LED ring shutter</b> (Shutter effects same as LED pixels)
15	0 – 255	<b>LED ring dimmer</b>