

DMX Control Modes

Standard Modus

Standard Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Grün
8	0 – 255	Blau
9	0 – 255	Weiß
10	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Zoom
14	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
15	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
16	0 – 255	LED Ring Dimmer
17	0 – 255	Pattern
18	0 – 255	Pattern Geschwindigkeit
19	0 – 255	LED Ring Pattern
20	0 – 255	LED Ring Pattern Geschwindigkeit
21	0 – 255	Control
22	0 – 255	Remote DMX Adresse

DMX Control Modes

Advanced Modus

Advanced Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Rot fein
8	0 – 255	Grün
9	0 – 255	Grün fein
10	0 – 255	Blau
11	0 – 255	Blau fein
12	0 – 255	Weiß
13	0 – 255	Weiß fein
14	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
15	0 – 255	Dimmer
16	0 – 255	Dimmer fein
17	0 – 255	CTO
18	0 – 255	Zoom
19	0 – 255	Zoom fein
20	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
21	0 – 255	LED Ring rot
22	0 – 255	LED Ring grün
23	0 – 255	LED Ring blau
24	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
25	0 – 255	LED Ring Dimmer
26	0 – 255	Pattern
27	0 – 255	Pattern Geschwindigkeit
28	0 – 255	LED Ring Pattern
29	0 – 255	LED Ring Pattern Geschwindigkeit
30	0 – 255	Control
31	0 – 255	Remote DMX Adresse

DMX Control Modes

Full Control Modus

Full Control Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Rot fein
8	0 – 255	Grün
9	0 – 255	Grün fein
10	0 – 255	Blau
11	0 – 255	Blau fein
12	0 – 255	Weiß
13	0 – 255	Weiß fein
14	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
15	0 – 255	Dimmer
16	0 – 255	Dimmer fein
17	0 – 255	CTO
18	0 – 255	Zoom
19	0 – 255	Zoom fein
20	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
21	0 – 255	LED Ring rot alle
22	0 – 255	LED Ring grün alle
23	0 – 255	LED Ring blau alle
24	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
25	0 – 255	LED Ring Dimmer
26	0 – 255	Rot 1
27	0 – 255	Grün 1
28	0 – 255	Blau 1
29	0 – 255	Weiß 1
30	0 – 255	Shutter 1
31	0 – 255	Dimmer 1
...	...	Rot ...
...	...	Grün ...
...	...	Blau ...
...	...	Weiß...

DMX Control Modes

...	...	Shutter...
...	...	Dimmer...
	0 – 255	Rot 19
135	0 – 255	Grün19
136	0 – 255	Blau 19
137	0 – 255	Weiß 19
138	0 – 255	Shutter 19
139	0 – 255	Dimmer 19
140	0 – 255	LED Ring 1, LED 1 rot
141	0 – 255	LED Ring 1, LED 1 grün
142	0 – 255	LED Ring 1, LED 1 blau
143	0 – 255	LED Ring 1, LED 2 rot
144	0 – 255	LED Ring 1, LED 2 grün
145	0 – 255	LED Ring 1, LED 2 blau
...	...	LED Ring ..., LED 1 rot
...	...	LED Ring ..., LED 1 grün
...	...	LED Ring ..., LED 1 blau
...	...	LED Ring ..., LED 2 rot
...	...	LED Ring ..., LED 2 grün
...	...	LED Ring ..., LED 2 blau
158	0 – 255	LED Ring 4, LED 1 rot
159	0 – 255	LED Ring 4, LED 1 grün
160	0 – 255	LED Ring 4, LED 1 blau
161	0 – 255	LED Ring 4, LED 2 rot
162	0 – 255	LED Ring 4, LED 2 grün
163	0 – 255	LED Ring 4, LED 2 blau
164	0 – 255	Control
165	0 – 255	Remote DMX Adresse

DMX Control Modes

Pixel Mapping Modus

Pixel Mapping Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Grün
8	0 – 255	Blau
9	0 – 255	Weiß
10	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Zoom
14	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
15	0 – 255	LED Ring rot alle
16	0 – 255	LED Ring grün alle
17	0 – 255	LED Ring blau alle
18	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
19	0 – 255	LED Ring Dimmer
20	0 – 255	Rot 1
21	0 – 255	Grün 1
22	0 – 255	Blau 1
23	0 – 255	Weiß 1
24	0 – 255	Shutter 1
25	0 – 255	Dimmer 1
...	...	Rot ...
...	...	Grün ...
...	...	Blau ...
...	...	Weiß ...
...	...	Shutter...
...	...	Dimmer...
128	0 – 255	Rot 19
129	0 – 255	Grün 19
130	0 – 255	Blau 19
131	0 – 255	Weiß 19

DMX Control Modes

132	0 – 255	Shutter 19
133	0 – 255	Dimmer 19
134	0 – 255	LED Ring Pattern
135	0 – 255	LED Ring Pattern Geschwindigkeit
136	0 – 255	Control
137	0 – 255	Remote DMX Adresse

DMX Control Modes

Pattern Control Modus

Pattern Control Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Grün
8	0 – 255	Blau
9	0 – 255	Weiß
10	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Zoom
14	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
15	0 – 255	LED Ring rot alle
16	0 – 255	LED Ring grün alle
17	0 – 255	LED Ring blau alle
18	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
19	0 – 255	LED Ring Dimmer
20	0 – 255	Rot 1
21	0 – 255	Grün 1
22	0 – 255	Blau 1
23	0 – 255	Weiß 1
24	0 – 255	Shutter 1
25	0 – 255	Dimmer 1
26	0 – 255	Pattern 1
27	0 – 255	Pattern 1 Geschwindigkeit
28	0 – 255	Rot 2
29	0 – 255	Grün 2
30	0 – 255	Blau 2
31	0 – 255	Weiß 2
32	0 – 255	Shutter 2
33	0 – 255	Dimmer 2
34	0 – 255	Pattern 2

DMX Control Modes

35	0 – 255	Pattern 2 Geschwindigkeit
36	0 – 255	Rot 3
37	0 – 255	Grün 3
38	0 – 255	Blau 3
39	0 – 255	Weiß 3
40	0 – 255	Shutter 3
41	0 – 255	Dimmer 3
42	0 – 255	Pattern 3
43	0 – 255	Pattern 3 Geschwindigkeit
44	0 – 255	LED Ring P1-rot
45	0 – 255	LED Ring P1-grün
46	0 – 255	LED Ring P1-blau
47	0 – 255	LED Ring P1-Shutter (Shuttereffekte wie LED Pixel)
48	0 – 255	LED Ring P1-Dimmer
49	0 – 255	LED Ring P1-Pattern
50	0 – 255	LED Ring P1-Pattern Geschwindigkeit
51	0 – 255	LED Ring P2-rot
52	0 – 255	LED Ring P2-grün
53	0 – 255	LED Ring P2-blau
54	0 – 255	LED Ring P2- Shutter (Shuttereffekte wie LED Pixel)
55	0 – 255	LED Ring P2-Dimmer
56	0 – 255	LED Ring P2-Pattern
57	0 – 255	LED Ring P2-Pattern Geschwindigkeit
58	0 – 255	Control
59	0 – 255	Remote DMX Adresse

DMX Control Modes

Compressed RGBW Modus

Compressed RGBW Modus		
CH	Wert	Funktion
1	0 – 255	Pan
2	0 – 255	Pan fein
3	0 – 255	Tilt
4	0 – 255	Tilt fein
5	0 – 255	Farbrad (Sh. Farbrad-Tabelle)
6	0 – 255	Rot
7	0 – 255	Grün
8	0 – 255	Blau
9	0 – 255	Weiß
10	0 – 255	Shuttereffekte (Sh. Shuttereffekt-Tabelle)
11	0 – 255	Dimmer
12	0 – 255	Zoom
13	0 – 255	LED Ring Farbrad (Sh. Farbrad-Tabelle)
14	0 – 255	LED Ring Shutter (Shuttereffekte wie LED Pixel)
15	0 – 255	LED Ring Dimmer