

DMX Control Modes


Standard Mode

Standard Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	White
10	0 – 255	Shutter effects (See shutter effects table)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Pattern
14	0 – 255	Pattern speed
15	0 – 255	Control
16	0 – 255	Remote DMX address

DMX Control Modes

Pixel Mapping Mode

Pixel Mapping Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	White
10	0 – 255	Shutter effects (See shutter effects table)
11	0 – 255	Dimmer
12	0 – 255	CTO
13	0 – 255	Pattern
14	0 – 255	Pattern speed
15	0 – 255	Red 1
16	0 – 255	Green 1
17	0 – 255	Blue 1
18	0 – 255	White 1
19	0 – 255	Shutter 1
20	0 – 255	Dimmer 1
...	...	Red ...
...	...	Green ...
...	...	Blue...
...	...	White...
...	...	Shutter...
...	...	Dimmer...
51	0 – 255	Red 7
52	0 – 255	Green 7
53	0 – 255	Blue 7
54	0 – 255	White 7
55	0 – 255	Shutter 7
56	0 – 255	Dimmer 7
57	0 – 255	Control
58	0 – 255	Remote DMX address



DMX Control Modes

Compressed RGB Mode

Compressed RGB Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	Shutter effects (See shutter effects table)
10	0 – 255	Dimmer

Compressed RGBW Mode

Compressed RGBW Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Green
8	0 – 255	Blue
9	0 – 255	White
10	0 – 255	Shutter effects (See shutter effects table)
11	0 – 255	Dimmer

DMX Control Modes

Advanced Mode

Advanced Mode		
CH	Value	Function
1	0 – 255	Pan
2	0 – 255	Pan fine
3	0 – 255	Tilt
4	0 – 255	Tilt fine
5	0 – 255	Color wheel (See color wheel table)
6	0 – 255	Red
7	0 – 255	Red fine
8	0 – 255	Green
9	0 – 255	Green fine
10	0 – 255	Blue
11	0 – 255	Blue fine
12	0 – 255	White
13	0 – 255	White fine
14	0 – 255	Shutter effects (See shutter effects table)
15	0 – 255	Dimmer
16	0 – 255	Dimmer fine
17	0 – 255	CTO
18	0 – 255	Pattern
19	0 – 255	Pattern speed
20	0 – 255	Control
21	0 – 255	Remote DMX address